



































# 32 Tone Chart for Sirens

							12V @20 c		24V @20°c		
							mA	dB(A)	mA	dB(A)	EN54-3 Min SPL @ 28Vdc @ Max Volume @ Loudest node dB(A)
1	14	11111		800 & 970Hz	2Hz (250ms~250ms)	BS Fire Tone	86	91	68	100	*
2	14	11110		800 & 970Hz	7Hz (7/s)	BS Fire Tone	86	93	68	101	*
3	14	11101		800 & 970Hz	1Hz (1/s)	BS Fire Tone	86	95	68	101	95
4	14	11100		2850Hz	Steady		93	95	82	110	*
5	4	11011		2400 ~ 2850Hz	7Hz		94	101	80	110	*
6	4	11010		2400 ~ 2850Hz	1Hz		92	104	80	110	*
7	14	11001		500 ~ 1200Hz	3s Sweep, 0.5s silence, then repeat	Dutch Fire Tone	84	95	70	98	97
8	14	11000		1200 ~ 500Hz	1Hz	DIN Tone	87	94	66	98	94
9	4	10111		2400 & 2850Hz	2Hz (250ms~250ms)		92	95	80	109	*
10	14	10110		970Hz	0.5Hz (1s On / 1s Off)		85	92	62	100	*
11	14	10101		800 & 970Hz	1Hz (500ms~500ms)	BS Fire Tone	85	92	68	100	*
12	4	10100		2850Hz	0.5Hz (1s On / 1s Off)		88	95	74	109	*
13	14	10011		970Hz	0.8Hz (250ms On / 1s Off)		83	91	58	96	*
14	14	10010		970Hz	Steady	BS Fire Tone	85	92	70	101	95
15	14	10001		554 & 440Hz	100ms ~ 400ms	French Fire Tone	87	93	62	93	*
16	16	10000		660Hz	3.3Hz (150ms On / 150ms Off)	Swedish Fire Tone	84	92	59	86	*
17	17	01111		660Hz	0.28Hz (1.8s On / 1.8s Off)	Swedish Fire Tone	84	93	62	88	*
18	18	01110		660Hz	0.05Hz (13s Off / 6.5Hz On)	Swedish Fire Tone	85	93	64	88	*
19	19	01101		660Hz	Steady	Swedish Fire Tone	84	93	64	89	*
20	20	01100		554 & 440Hz	0.5Hz (1s On / 1s Off)	Swedish Fire Tone	86	93	63	96	*
21	21	01011		660Hz	1Hz (500ms ~ 500ms)	Swedish Fire Tone	84	92	60		*
22	14	01010		2850Hz	4Hz (150ms On / 100ms Off)	Pelican Crossing	90	94	72	109	*
23	14	01001		800 ~ 970Hz	50Hz	BS Fire Tone	85	92	68	101	*
24	4	01000		2400 ~ 2850Hz	50Hz		93	101	75	110	*
25	25	00111		970Hz	3 x 500ms pulses followed by 1.5s silence then repeat	ISO 8201	83	92	64	99	*
26	26	00110		2850Hz	3 x 500ms pulses followed by 1.5s silence then repeat	ISO 8201	84	94	70	108	*
27	27	00101		4000Hz	Steady		83	91	85	83	*
28	10	00100		800 & 970Hz	2Hz (250ms ~ 250ms)	BS Fire Tone	86	91	67	100	*
29	33	00011		990 & 650Hz	2Hz (250ms ~ 250ms) (Symphoni Tones)	BS Fire Tone	87	95	71	99	96
30	35	00010		510 & 610Hz	2Hz (250ms ~ 250ms) (Squashni Micro Tones)	BS Fire Tone	86	91	65	96	92
31	31	00001		300 ~ 1200Hz	1Hz		87	95	71	96	*
32	32	00000		4000Hz	Steady		86	92	85	83	*